

THANK YOU FOR CHOOSING A MORLEY STEVE VAI BAD HORSE 2 CONTOUR WAH. YOU NOW OWN THE BEST PEDAL MADE!

Please take a few minutes to familiarize yourself with the features of your new pedal. We hope you enjoy using it as much as we enjoyed building it.

ABOUT OUR ELECTRO-OPTICAL CIRCUITRY:

An LED (Light Emitting Diode) shines on an LDR (Light Dependent Resistor). A shutter alters light between the two components controlling functions like Wah, volume and switching. Electro-Optical design ensures smooth pedal control without unwanted noise typical with potentiometer (pot) controlled pedals.

ABOUT THE CONNECTIONS:

9V: To ensure noise free operation, ONLY Morley's 9VDC 300 milliamp regulated adapter should be used

IN: Input jack. Plug instrument into this jack using 1/4" guitar cable.

OUT: Connect amplifier to this jack using a 1/4" guitar cable.

USING AN AC ADAPTER:

All Morley pedals use Morley's 9VDC 300 milliamp regulated adapter. Center pin polarity is negative. **Using a non-regulated adapter could cause a low frequency hum in your amplifier.** Using an adapter with the wrong polarity may damage the pedal.

USING A BATTERY:

All Morley pedals are designed to use one 9V battery when not using an adapter. We suggest you use a good quality alkaline battery. To prolong battery life, unplug your cord completely from the input jack when not using the pedal. When the pedal is not used for extended periods, remove the battery from the pedal. Our "Quick Clip" Battery door allows easy access to battery compartment.

ONE YEAR WARRANTY

All Morley® pedals are warranted for one year with copy of dated purchase receipt. To obtain warranty service, contact store where pedal was purchased or email contact@morleybtech.com

BAD HORSE 2 FEATURES (MODEL VAI-2):

- **SWITCHLESS OPERATION:** Simply Step on to engage Wah and step off to go to bypass.
- **CONTOUR SWITCH:** Selects a second Wah mode
- **LEVEL:** Adjusts the output of the Wah in Contour Mode
- **CONTOUR:** Adjust the frequency of the Wah when in Contour Mode

VAI-2 SPECIFICATIONS:

Power: 9V Battery or 9VDC 300mA regulated (center pin negative)

Indicator (right): Wah on LED on, Wah off LED off

Indicator (left): Contour Wah on LED on

Dimensions: 9.13" L x 5.88" W x 2.75" H

Current Draw: 12 mA @ 9VDC

Weight: 3.3 lb./ 1.51 kg

www.morleyproducts.com

